

BM 3804FM

MULTI-ZONE EMERGENCY FIREMAN MICROPHONE

DESCRIPTION

BM 3804FM is a wall mount emergency microphone exclusively dedicated for the RCF DXT 3000 system. It can be directly connected to the MX 3250 main unit through a fourpair J-type fire-rated cable. If more than one console are connected to the system (interlocked one another), in daisy-chained link, BM 3804FM shall be the first one, configured as emergency microphone and directly powered by the MX 3250 main unit, while the second, the third and the fourth need 24 V DC adapters (500 mA, e.g. RCF AC AD2405, optional).



FEATURES

- Handheld dynamic microphone with PTT button
- Complete self-diagnostic
- Power supply voltage from the BUS (first microphone only) or from 24V DC local input
- Pre-recorded message activation
- Alert and evacuation indications
- Wall-mounted metallic box (color: red, RAL 3000) with glass



TECHNICAL SPECIFICATIONS

Microphone specifications	Туре:	Dynamic
	Directivity:	Omnidirectional
	Frequency Response (-3dB):	300 Hz ÷ 6000 kHz
	Output impedance (ohm):	500.00 ohm
Console specifications	Console Type:	Emergency
	Working with	DXT 3000
	General call:	Yes
	Selective call:	Yes
	Preamplified:	Yes
	LED indicators:	Yes
Power requirement	Operating voltage:	24.00V ~ Hz
Connections	Connectors:	RJ45
	Cable:	J-Type fire-rated
	Daisy-chain:	Yes
	Max number in daisy-chain:	4
	Interlock:	Yes
Functionalities	Priority:	Yes
	Chime tone generator:	Yes
Accessories	Cable included:	Yes
	Cable length (m):	5
Standard compliance	EN54-16 certified:	Yes
	CE marking:	Yes
	CPR number:	0068-CPR-007/2015
Physical specifications	Cabinet/Case Material:	Metal
	Color:	Red - RAL 3000
Size	Height:	360 mm / 14.17 inches
	Width:	360 mm / 14.17 inches
	Depth:	129 mm / 5.08 inches
	Weight:	6.9 kg / 15.21 lbs
Shipping informations	Package Height:	130 mm / 5.12 inches
	Package Width:	360 mm / 14.17 inches
	Package Depth:	360 mm / 14.17 inches

PART NUMBER

14380037


BM 3804FM

EAN 8024530012885






DRAWINGS



PANELS

Front panel



CONFIGURATIONS

Without BE 3806

With BE 3806

